

Before ProVision Security Solutions can begin our installation process, certain aspects of your build-out must be complete. The following information outlines these requirements. Please review these with your contractor and/or other vendors. For detailed questions about the additional requirements, please contact your project coordinator at 866.315.0777.

1. Internet Access: Broadband access (DSL, cable, etc.) with a static IP address. The static IP address is an address that does not change and is required for remote computer support and remote viewing of the CCTV system through the DVR. Most Internet Service Providers (ISP) that provide broadband access also provide a modem with their service. They typically do not provide a router, but if they do, it will need a built-in 10/100 switch and a 4-port switch. Also ask your ISP for the user name and password to access the router, we will need to port forward to the DVR for remote access.

A router allows multiple PCs, and other devices, such as the DVR, to access the Internet simultaneously. It also provides a firewall to protect the local network from malicious attacks. If your ISP cannot provide a router with the requirements listed above, we will include one in your price quote.

2. Door Strike: For this component, you should contact a local, and trusted, locksmith. Your builder may have a preferred vendor for this type of work. It's best to contact the locksmith early in the build-out; doing so will allow any special order items to arrive on time. **The recommended door latch is a normally secure electronic door strike. PSS strongly encourages the installation of the electronic door strike, rather than a magnetic lock.**

The requirements for the electronic door strike are:

- The strike will need to operate off 12 or 24 VDC.
- The locksmith will need to provide a 12 or 24 VDC plug-in transformer, such as a Revere Industries RTD12/5RT, or equivalent, that meets the specifications of the strike manufacturer. Revere Industries products are available at [Wm. B. Allen Supply Co., Inc.](#)
- Provide and install armored loop, if needed.
- Install the control cable from the strike to the duplex outlet above the door and test lock.

It is not recommended by PSS, but if a magnetic lock is required, than an override key needs to be installed on the exterior of the door. This allows entry to the club when the access control program is not available, or provides an additional keyed entrance, if necessary. A removable mullion is preferred for double door applications to allow for large pieces to more easily be transported into your facility.

For emergency access to the club, **local authorities may require the installation of a Knock-Box**. This box stores a spare key on the exterior of the building. To verify if this is a requirement, please contact both your local police and fire departments. If a knock-box is required, the local authorities can recommend where to purchase one.

Note: The member door or doors (there may be 1 or 2) require a free exiting device, such as a crash bar or paddle. Plus, member doors **MUST swing outward**. If the door currently doesn't swing outward, adjustments will need to be made prior to installation.

3. Door Latch Guard: A latch protector prevents intruders from tampering with the lock spring mechanism or bolt assembly, by shielding that portion of the door. This component is installed between the shield of the doorknob and the door, so that the angled lip lays over the edge of the door. The latch protector may be used on doors with locking assemblies on either the right or left side of the door.

4. Electrical Outlets: The outlet requirements are listed below:

- One duplex 110 outlet above **each** member entrance door. This outlet will be used by the electronic door strike and the access control system.
- Please confirm with your tanning bed manufacturer the outlet specifications required to operate your tanning beds.
- One double duplex outlet in the office, near the computer desk. The outlet must be within 3 feet of the final placement of the desk that will hold the club's main computer, and it should be installed at standard outlet height.
- One duplex outlet near **each** television. The outlets must be within the television electrical cord limits, which is generally within 7 feet of the unit.
- One double duplex outlet within 3 feet of the final placement of the DVR, security panel, sound amplifier, and CCTV power supply.

Important: Permanent power is required prior to installation.

5. Voice over Cable: The only way we can allow digital phone setup is if the VoC (Voice over Cable) provider can supply a 12-hour backup for the phone line (which is also tied to the security alarm panel) in the case of a power outage. POTS (Plain Old Telephone Service) is virtually immune to power outages, simply due to the fact that it draws power from the central office, and all lines are supported by battery backup. If you opt for VoC, VoIP, or VoS, you will need a 12-hour battery backup. PSS recommends a cellular backup system be purchased and installed in conjunction with this type of service. This will use cellular service for the alarm panel in the event of power failure. Please ask your project coordinator for a price for this product and service.

6. Low Voltage Wiring: A phone jack needs to be installed within 3 feet of the final placement of the security panel (which will normally be located in the main office). The cable used must be a home-run cable. To allow for equipment stacking, the phone jack should be installed next to the double duplex outlets in the office.

The phone line for the security alarm cannot be shared by other devices, e.g., courtesy phone, DSL, fax, or credit card terminal. For these items, a second telephone jack, and perhaps a third, will need to be installed in the office. The location of these additional outlets is determined by the final placement of your furnishings.

Suggested telephone jack locations: one by the fax and credit card machines, one jack in office for the main line, one jack in the main gym area for a courtesy phone, 46" AFF, and one jack at the final location of the security system that will be located in the office near the placement of the DVR.

Note: If the Internet router/switch (which will be located in the office) is more than 5 feet from a second computer, DVR, network printer, or card access vending machine, additional computer lines (such as a CAT 5 E cable) will need to be installed prior to installation.

7. Security System: The security panel will be located in the main office. A motion detector will be installed in the office, protecting the security panel from tampering. The power source for the security panel will be supplied by a double duplex outlet (see *3. Electrical Outlets* for details.)

The security system will be integrated with an Alarm Monitoring Service. This monthly monitoring service is free of charge as long as the equipment is purchased through provision security.

Wireless panic buttons are powered by (2) Energizer 386, 1.5V, Silver Oxide Cells. You will need to change the batteries when the LED on the pendant pulses 1.5 times per second, or when the panel instructs you to do so. Please keep sufficient batteries on hand to replace all units at one time.

Wireless door contacts are powered by a DL123A, 3 Volt Lithium Battery. This battery will need to be changed when the panel instructs you to do so. Please keep one backup battery per unit on hand for replacement.

Wireless glass breaks are powered by a DL123A, 3 Volt Lithium Battery. This battery will need to be changed when the panel instructs you to do so. Please keep one backup battery per unit on hand for replacement. The glass break is omni-directional, which means it measures the decibel level in all directions. It protects plate glass from 3/32" to 1/4", up to 25 feet. It protects tempered, wired, or laminated glass from 1/8" to 1/4", up to 20 feet. **Glass break detectors are sensitive to high decibel sounds. Because of this, they are not installed in your main workout areas, where equipment noise can cause false alarms. They are generally installed in storage rooms or back entrance areas that are separated from the rest of your club.**

Note: Some local municipalities require a permit to operate a security system. Check with your local authorities to see if this is the case in your area.

In addition to the security system components, the following items **must be installed** on the premises in accordance with Anytime Fitness compliance requirements:

(A) A telephone for 911 call access.

(B) A sign in plain view with an advisory warning that indicates members of a non-staffed health spa should be aware that working out alone may pose risks to their health and safety.

8. Tailgate System: This system is installed 10 inches AFF, with one unit on either side of the member entrance door(s). The doorframe will need at least 2.5 inches of horizontal clearance on both sides of the door for the two units to be installed; the units are approximately 36 inches long. A 3/4 inch hole, with bushings, will need to be cut into the top of the vertical door frame, on both sides, with a pull string to the accessible ceiling space, or to a low voltage frame next to the duplex 110V outlet if an open ceiling.

9. TV Mounting: Unistruts may be required in ceiling installations where the trusses are made out of metal. The unistruts must be supplied by the landlord or contractor. Unistruts typically attach at the bottom of the metal truss and span across two trusses, and the opening must face the floor. Unistrut specifications are 1 5/8" x 1 5/8" - 12 gauge. *Minimum two points of contact required.*

Very Important: Wall mounts require an external wall plate that is designed for use on 25 gauge or heavier metal studs to safely span the load between two studs (applies to 16'', 20'', or 24'' center). Wall plates can also be used on wood studs. A typical commercial building uses the heavier gauge studs mainly on the perimeter (outside) walls and thinner gauge for internal walls. Please check with your contractor regarding the design and gauge of the metal studs.

The exact measurements of your televisions, along with the model name, number, and manufacturer, must be listed on the Pre-Quote Club Profile. Or, if you prefer, this information can be sent directly to your project coordinator. These measurements will help us determine which TV mounts are necessary for installation.

10. Installation of Equipment: The installation will begin only after the flooring/carpeting and the painting has been completed.

11. Alarm Permits: Contact your local authorities for information regarding alarm permits. Occasionally emergency professionals require businesses to apply for an alarm permit. If an alarm permit is mandated by your local municipality, you will be required to apply for and purchase this permit for the operation of your alarm system.

12. General: Conduit systems may be a requirement of your State and / or local regulations. Contact your general construction manager to see if this is a requirement. Provision Security does not install conduit systems.

If you have any questions pertaining to the requirements outlined in this document, please contact your Project Coordinator at 866.315.0777.